



Sigen Energy Gateway Home Series

- Seamless switch to backup mode, worry-free energy usage
- Ready for generator, heat pump or other controllable loads
- Support both whole home backup & partial home backup
- 350 ms reverse power flow protection of grid & generator
- Uninterrupted power supply through PV+ESS/grid/generator
- Support rear wiring for more flexible installation

Sigen Energy Gateway for Australia

Sigen Gateway	Home SP AU	Home TP AU	Units
Grid Connection			
Grid connection type	Single phase	Three phase	
Nominal AC input / output voltage	220 / 230 / 240	380 / 400	V
Nominal AC input / output current	54.6	45.6	A
Nominal current of circuit breaker ¹	63		A
Nominal AC input / output power	12	30	kW
Nominal AC frequency	50 / 60		Hz
Disruption time of backup switch ²	0		ms
AC Output to Backup Port			
Nominal AC output voltage	220 / 230 / 240	380 / 400	V
Nominal AC output current	54.6	45.6	A
Nominal current of circuit breaker ¹	63		A
Nominal AC output power	12	30	kW
Nominal AC frequency	50 / 60		Hz
Overvoltage category	III		
AC Output to Non-Backup Port			
Nominal AC output voltage	220 / 230 / 240	380 / 400	V
Nominal AC output current	54.6	45.6	A
Nominal AC output power	12	30	kW
Nominal AC frequency	50 / 60		Hz
Inverter Connection			
Nominal AC voltage	220 / 230 / 240	380 / 400	V
Nominal AC input current	54.6 (INV1), 32 (INV2) ³	45.6 (INV1), 32 (INV2) ⁴	A
Nominal current of circuit breaker ¹	63 (INV1), 40 (INV2)		A
Smart Port Connection			
Generator output voltage	220 / 230 / 240	380 / 400	V
Nominal input / output current	54.6	45.6	A
Nominal current of circuit breaker ¹	63		A
Nominal AC input / output power	12	30	kW
Generator 2-wire start	Supported		
General Data			
Dimensions (W / H / D)	450 / 570 / 197 (without decorative cover)		mm
Weight	22.5 (without decorative cover)	25.5 (without decorative cover)	kg
Storage temperature range	-40 ~ 70		°C
Operating temperature range	-30 ~ 55		°C
Relative humidity range	0% ~ 100%		
Max. operation altitude	4000		m
Cooling	Natural convection		
Ingress protection rating	IP54		
Communication	Fast Ethernet , RS485, dry contact		
Installation method	Wall mounted, rear wiring supported		

1. The circuit breaker can be adjusted according to actual requirements and cable specifications.
2. This refers to the load-side disruption time, to achieve this functionality Sigen Energy Gateway needs to be used together with Sigen Energy Controller and Sigen Battery. Test conditions: In the open-circuit state of the power grid, the nominal power of the Sigen Energy Controller is higher than the total power of the backup loads.
3. For Sigen single phase inverter products, 8.0-12.0 kW inverters should be connected to the INV1 port, 3.0-6.0 kW inverters should be connected to the INV2 port. The sum of the parallel power of the Sigen inverters cannot exceed 12 kW.
4. For Sigen three phase inverter products, 15.0-30.0 kW inverters should be connected to the INV1 port, 5.0-15.0 kW inverters should be connected to the INV2 port. The sum of the parallel power of the Sigen inverters cannot exceed 30 kW.