



Product advantages

- 01 More safety features included
- 02 Endless freedom
- 03 Optimal performance as standard

The Fronius Symo Advanced impresses not only with levels of performance and flexibility that have been proven a million times over, but also with its new equipment. The highlight in terms of safety is the integrated Fronius Arc Guard technology, which ensures the Fronius Symo Advanced exceeds the highest standards and is the future-proof and reliable choice for commercial photovoltaic systems of any size.

Fronius Symo Advanced. Designed to rely on.

Developed with safety in mind:

The Fronius Symo Advanced opens the next chapter in the Fronius SnapINverter portfolio. Performance proven a million times over meets new safety technology, making the Fronius Symo Advanced more than ever a future-proof choice for installers and their customers.

01 More safety features included

Detect, intervene, learn — the new Fronius Arc Guard technology follows this principle to protect against dangerous arcs. The algorithm developed by Fronius reliably detects arcing and shuts down the photovoltaic system before a fire can occur. The Fronius Arc Guard is being continuously trained by the manufacturer to make the Arc Fault Circuit Interrupter more precise and to optimize system protection.

02 Endless freedom

Easily plan complex roofs thanks to SuperFlex Design. The PV modules can be flexibly aligned and connected as the Fronius Symo Advanced is able to handle a wide range of input voltages as well as very high PV module currents.

03 Optimal performance as standard


Maximum yield even when the PV modules are partially in the shade is possible thanks to the Dynamic Peak Manager feature of the Fronius Symo Advanced. The intelligent software-based shade management tool is installed as standard and requires no additional components.


Fronius Symo Advanced

Impressive power data


The Fronius Symo Advanced impresses with its flexible system design and the highest safety standards.


Efficiency





Power derating





Technical data

10.0 / 12.5 / 15.0 kW

Number of MPP trackers 2 2 2 2 2 2 2 2 2	10.0 / 12.5 / 15.0 KVV				Symo A	no Advanced				
Max. Injust current (lude map)				10.0-3-M		12.5	12.5-3-M		15.0-3-M	
Max. input ourrent (I _{00 max})		Number of MPP trackers								
Max. programment A 43.5 43.5 510				MPPT1	MPPT2	MPPT1	MPPT2	MPPT1	MPPT2	
Mark		Max. input current (I _{dc max})	А	27.0	16.5 1	27.0	16.5 1	33.0	27.0	
Max. unray thors carried countered to the print countered to the p			А	43.5		43.5		51.0		
				MPPT1	MPPT2	MPPT1	MPPT2	MPPT1	MPPT2	
Usable MPP voltage range (at rated power) V 200-800 320-80	is a	Max. array short circuit current MPPT1/MPPT2 (I _{sc pv}) ²	А	55.7	34	55.7	34	68	55.7	
Usable MPP voltage range (at rated power) V 200-800 320-80	ut dat		V	200–1000		200–1000		200-	1000	
MPP Valtage range (at rated power) V 270-800 320	Inp		٧	200		200		200		
Compage Comp		Usable MPP voltage range	V	200-800		200-800		200-800		
Number of DC connections 3			V	270-800						
Max. PV generator output (Pdc max) Wpeak 15,000 18,800 22,500										
AC nominal output (Pac,r) W 10,000 12,500 15,000									-	
Max. output power / rated apparent power NA 10,000 12,500 15,000		Max. PV generator output (P _{dc max})	Wpeak	15,0	000	18,8	300	22,	500	
Max. output power / rated apparent power NA 10,000 12,500 15,000										
10,000 12,500 18,000 1		AC nominal output (Pac,r)	W	10,000		12,500		15,000		
Prequency (trequency range) H2 SO / 80 (45 - 65) SO / 80 (45 - 65) SO / 80 (45 - 65) Total harmonic distortion % < 1.75 < 2.0 < 1.5	a a		VA	·		12,500		15,000		
Prequency (trequency range) H2 SO / 80 (45 - 65) SO / 80 (45 - 65) SO / 80 (45 - 65) Total harmonic distortion % < 1.75 < 2.0 < 1.5	dat			380 VAC	400 VAC	380 VAC	400 VAC	380 Vac	400 VAC	
Prequency (trequency range) H2 SO / 80 (45 - 65) SO / 80 (45 - 65) SO / 80 (45 - 65) Total harmonic distortion % < 1.75 < 2.0 < 1.5	ont	AC output current (I _{ac nom})	А	15.2	14.4	18.9	18	22.7	21.7	
Prequency (trequency range) H2 SO / 80 (45 - 65) SO / 80 (45 - 65) SO / 80 (45 - 65) Total harmonic distortion % < 1.75 < 2.0 < 1.5	ntp	Grid connection (voltage range)		3-NPE 400 V / 230 V or 3~NPE 380 V / 220 V (+20 % / -30 %)					%)	
Power factor (cos \(\phi_{\text{ac,r}} \) O-1 \(\text{ind.} \text{ / cap.} \)	0	Frequency (frequency range)	Hz	50 / 60 (45 - 65)		50 / 60	(45 - 65)	50 / 60	(45 - 65)	
Dimensions (height x width x depth) mm 725 x 510 x 225		Total harmonic distortion	%	< 1.75 < 2.0			< '	1.5		
Weight (inverter/with packaging) kg 35.4/38.4 35.4/38.4 41.96/44.96		Power factor (cos φ _{ac,r})		0-1 ind. / cap.						
Protection class		Dimensions (height x width x depth)	mm	725 x 510 x 225						
Safety class		Weight (inverter/with packaging)	kg	35.4/38.4		35.4	/38.4	41.96	/44.96	
DC AC DC AC DC AC AC DC AC A		Protection class		IP 66		IP 66		IP 66		
Overvoltage category (DC/AC)3		Safety class		1		1			L	
Night consumption W <1 <1 <1				DC	AC	DC	AC	DC	AC	
Inverter concept		Overvoltage category (DC/AC) ³		2	3	2	3	2	3	
Active Cooling technology Installation Indoor and outdoor installation		Night consumption	W	<	:1	<	1	<	1	
Max. altitude above sea level m 2,000/3,400 2,000/3,400 2,000/3,400 DC connection technology mm² 6x DC + and 6x DC screw terminals 2.5 - 16 mm² AC connection technology mm² 5-pin AC screw terminals 2.5 - 16 mm² EC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023		Inverter concept		Transformerless						
Max. altitude above sea level m 2,000/3,400 2,000/3,400 2,000/3,400 DC connection technology mm² 6x DC + and 6x DC screw terminals 2.5 - 16 mm² AC connection technology mm² 5-pin AC screw terminals 2.5 - 16 mm² EC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023	ata	Cooling		Active Cooling technology						
Max. altitude above sea level m 2,000/3,400 2,000/3,400 2,000/3,400 DC connection technology mm² 6x DC + and 6x DC screw terminals 2.5 - 16 mm² AC connection technology mm² 5-pin AC screw terminals 2.5 - 16 mm² EC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023	al d	Installation		Iı		ndoor and outdoor installation		on		
Max. altitude above sea level m 2,000/3,400 2,000/3,400 2,000/3,400 DC connection technology mm² 6x DC + and 6x DC screw terminals 2.5 - 16 mm² AC connection technology mm² 5-pin AC screw terminals 2.5 - 16 mm² EC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023	ner	Ambient temperature range	°C	-25 - +60		-25 - +60		-25 - +60		
Max. altitude above sea level m 2,000/3,400 2,000/3,400 2,000/3,400 DC connection technology mm² 6x DC+ and 6x DC screw terminals 2.5 - 16 mm² AC connection technology mm² 5-pin AC screw terminals 2.5 - 16 mm² Certificates and compliance with standards IEC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023	Ge	Permissible humidity	%	0-100		0-100		0-100		
DC connection technology mm² 6x DC+ and 6x DC screw terminals 2.5 - 16 mm² AC connection technology mm² 5-pin AC screw terminals 2.5 - 16mm2 Certificates and compliance with standards IEC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023				unres		stricted / restricted voltage r		range		
AC connection technology mm ² 5-pin AC screw terminals 2.5 - 16mm2 IEC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023		Max. altitude above sea level	m	2,000/3,400		2,000/3,400 2,000/3,400			/3,400	
IEC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023		DC connection technology	mm²	6x DC+ and 6x DC screw terminals 2.5 - 16 mm²						
Certificates and compliance with standards G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023		AC connection technology	mm²		5-pin	AC screw ter	minals 2.5 - 16	Smm2		
Country of manufacture Austria				G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2,			0-16,			
		Country of manufacture		Austria						

 $^{^{\}mathbf{1}}$ 14.0 A at voltages < 420 V

² Isc pv = Isc max. \geq Isc (STC) x 1.25 according to e.g. IEC 60364-7-712, NEC 2020, AS/NZS 5033:2021.

³ In line with IEC 62109-1. DIN rail for optional surge protection device type 1 + 2 or type 2 present. For further information on the availability of the inverters in your country, please visit www.fronius.com.

Modbus RTU SunSpec or meter connection

			Symo Advanced				
			10.0-3-M	12.5-3-M	15.0-3-M		
ς	Max. efficiency	%	97.8	97.8	97.9		
Efficiency	Europ. efficiency (ηEU)	%	97.1	97.4	97.6		
E.	MPP adaptation efficiency	%	> 99.9	> 99.9	> 99.9		
	Arc Fault Circuit Interrupter - AFCI (Fronius Arc Guard)		Integrated				
Protection devices	DC isolation measurement		Integrated				
rotection devices	Overload performance		Operating point shift, power limiter				
rot de	DC disconnector		Integrated				
ш.	Reverse polarity protection		Integrated				
	RCMU		Integrated				
	WLAN / Ethernet LAN		Fronius Solar.web, Modbus TCP SunSpec, Fronius Solar API (JSON)				
	6 inputs and 4 digital inputs/outputs		Connection to ripple control receiver				
Interfaces	USB (type A socket)*		Datalogging, inverter updating using a USB thumb drive				
	2x RS422 (RJ45 socket) ⁴		Fronius Solar Net				
	Message output ⁴		Energy management (potential-free relay output)				
	Datalogger and web server		Integrated				
	External input ⁴		So-Meter Interface / Input for overvoltage protection				

⁴ Also available in a light version.

RS485

Technical data 17.5 / 20.0 kW

17.5) / 20.0 KVV	Symo Advanced						
			17.5-3-M 20.0-3-M			-3-M		
	Number of MPP trackers		2		2			
			MPPT1	MPPT2	MPPT1	MPPT2		
	Max. input current (I _{dc max})	А	33.0	27.0	33.0	27.0		
	Max. usable input current (Idc max MPPT 1+2)	А	51.0		51.0			
			MPPT1	MPPT2	MPPT1	MPPT2		
E E	Max. array short circuit current MPPT1/MPPT2 (I _{SC pv}) ²	А	68	55.7	68	55.7		
Input data	DC input voltage range (Udc min - Udc max)	٧	200-1000		200-	1000		
Inp	Feed-in start-up input voltage (Udc start)	٧	200		200			
	Usable MPP voltage range	V	200-	800	200-800			
	MPP Voltage range (at rated power) (Umpp min - Umpp max)	V	370-800		420-800			
			MPPT1	MPPT2	MPPT1	MPPT2		
	Number of DC connections		3	3	3	3		
	Max. PV generator output (P _{dc max})	Wpeak	26,3	500	30,0	000		
		347	17500					
	AC nominal output (Pac,r)	W	17,500		20,000			
_	Max. output power / rated apparent power	VA	17,500		20,000			
Output data			380 Vac	400 VAC	380 VAC	400 VAC		
out.	AC output current (I _{ac nom})	А	26.5	25.3	30.3 28.9			
utk	Grid connection (voltage range)		3-NPE 400 V / 230 V or 3~NPE 380 V / 220 V (+20 % / -30 %)					
0	Frequency (frequency range)	Hz	50 / 60 (45 - 65)		50 / 60 (45 - 65)		
	Total harmonic distortion	%	< 1	.5	< 1.	25		
	Power factor (cos φ _{ac,r})			0–1 in	d. / cap.			
	Dimensions (height x width x depth)	mm	725 x 510 x 225					
	Weight (inverter/with packaging)	kg	41.96/		41.96/	44 96		
	Protection class	1,6	IP 66		IP 66			
	Safety class		1		1			
			DC	AC	DC	AC		
	Overvoltage category (DC/AC) ³		2	3	2	3		
	Night consumption	W	<	1	<	1		
	Inverter concept		Transformerless					
ata	Cooling		Active Cooling technology					
General data	Installation		Indoor and outdoor installation					
nera	Ambient temperature range	°C	-25 - +60		-25 - +60			
Ge	Permissible humidity	%	0-1	.00	0-1	0-100		
			unrestricted / restricted voltage range					
	Max. altitude above sea level	m	2,000/3,400 2,000/3,400			•		
	DC connection technology	mm²	6x DC+ and 6x DC screw terminals 2.5 - 16 mm²					
	AC connection technology	mm²	5-pin AC screw terminals 2.5 - 16mm2					
	Certificates and compliance with standards		IEC 62109-1/-2, IEC 62116, IEC 61727, VDE 0126-1-1/A1, VDE AR-N 4105, G98/1, G99/1, AS/NZS 4777.2, UNE 206007-1, CEI 0-21, CEI 0-16, NRS 097-2-1, TOR Erzeuger Typ A, VDE AR-N 4110, EN 50549-1/-2, IEC 61683, IEC60068, IEC 63027:2023					
	Country of manufacture		Austria					
			Addition					

² Isc pv = Isc max. ≥ Isc (STC) x 1.25 according to e.g. IEC 60364-7-712, NEC 2020, AS/NZS 5033:2021.

³ In line with IEC 62109-1. DIN rail for optional surge protection device type 1 + 2 or type 2 present.
For further information on the availability of the inverters in your country, please visit www.fronius.com.

			Symo Advanced		
			17.5-3-M	20.0-3-M	
ıcy	Max. efficiency	%	97.9	97.9	
Efficiency	Europ. efficiency (ηEU)	%	97.6	97.6	
Ħ	MPP adaptation efficiency	%	> 99.9	> 99.9	
	Arc Fault Circuit Interrupter - AFCI		Integr	rated	

Arc Fault Circuit Interrupter - AFCI (Fronius Arc Guard)	Integrated		
DC isolation measurement	Integrated		
Overload performance	Operating point shift, power limiter		
DC disconnector	Integrated		
Reverse polarity protection	Integrated		
RCMU	Integrated		

	WLAN / Ethernet LAN	Fronius Solar.web, Modbus TCP SunSpec, Fronius Solar API (JSON)		
	6 inputs and 4 digital inputs/outputs	Connection to ripple control receiver		
ses	USB (type A socket)4	Datalogging, inverter updating using a USB thumb drive		
Interfaces	2x RS422 (RJ45 socket)4	Fronius Solar Net		
	Message output ⁴	Energy management (potential-free relay output)		
	Datalogger and web server	Integrated		
	External input 4	So-Meter Interface / Input for overvoltage protection		
	RS485	Modbus RTU SunSpec or meter connection		

⁴ Also available in a light version.

Further information: www.fronius.com/commercial-inverters